
#### **BLOOD GLUCOSE MONITORING SYSTEM**


## **QUICK REFERENCE GUIDE**

# DᢤΔGΛOSTIC® GOLD SYSTEM


This quick instruction for use will help you to set up and prepare your glucose meter for performing a test. For detailed information, see the Instruction for use included to the set Diagnostic Gold System.

### 1. GLUCOSE METER DESCRIPTION







## 2. STARTING THE DEVICE



Open the battery cover, moving forward a dimple in it.




Place the batteries, remember about the correct polarity + -.




Slide battery cover back.


#### 3. SETTING THE DATE AND TIME




Turn the meter on by pressing  $\circlearrowleft$ , then hold  $\circlearrowleft$  for 3 sec. Turn on (ON) or turn off (OFF) beep sound using > or < buttons. Press  $\circlearrowleft$  to confim the settings.




Set up a hypoglycemic alarm among the values 60, 70, 80 mg / dL or turn it OFF by pressing > or <. Press & to confirm the settings.




Use > or < to set the year. Press © to confirm the settings.



Use > or < to set the format: month and date (m-d) or date and month (d-m). Press  $\circ$  to confirm the settings.




Use > or < to set the month and date. Press  $\circ$  to confirm the settings. Use > or < to set the time. Press  $\circ$  to confirm the settings.




Use > or < to set time format. Confirm the settings. Use > or < to set an hour. Confirm the settings.


# 4. PREPARING THE LANCING DEVICE




Twist and remove the cap from the lancing device.




Insert the lancet into the lancet holder




Twist and remove the lancet cap.



Put and tighten the cap back onto the lancing device




Set the puncture depth by turning the end of the cap.




Pull back the movable part until you hear a click


### **5. PERFORMING THE TEST**




Before performing the test, wash your hands thoroughly and dry them.




Put down the date when the vial has been firstly opened. Remove the strip from vial and tightly seal the cap. Put down the date of the first vial opening.




Insert a test strip.




A flashing **●** means that the device is ready to take a blood sample. Press > once or twice to mark a test as pre-meal **♡** or post-meal **♡**.




Massage vigorously the place of blood sampling.




Firmly press the lancing device to the fingertip and press the release button. Click sound means that the puncture has been performed.




Apply the glucose meter with a strip to a drop of blood. Blood will be automatically sucked into the test strip.




Make sure that the confirmation window is completely filled with blood.



As soon as the confirmation window will be filled with blood, the glucose meter will start counting down from 5 to 1.



Glucose meter will display your result and save it automatically in the memory.



Glucose meter will automatically turn off after removing the test strip.





Rev. 2021.03.10 v1